

DESCRIPTION:

Rymax Contact Cleaner is recommended for the removal of light oils, dust, dirt and fingerprints from electrical connectors, printed circuit boards, relays, switches, scales, timers and other sensitive electrical and electronic equipment.

Applications

- Switches
- Batteries
- Contact Points
- Printed Circuit Board Switches
- Multiple Sockets

How to use?

Before use, carefully read the directions on the packaging and act accordingly. The aerosol should have room temperature. Best processing temperature 5 to 30°C.

- Thoroughly clean, degrease, and dry the surface.
- Shake the can before use.
- Spray the product at a distance of approximately 20-25 cm from the surface.
- Apply the spray as required.
- If using the product as a contact spray, do not switch on electrical installations until the spray has evaporated.
- If using the product as a rust remover, wait for 5 to 10 minutes.
- Ensure adequate ventilation when using the product.



BENEFITS:

- Non conductive
- Leaves no residue
- Non corrosive
- Powerful jetspray
- High dissolving properties
- Non-conductive
- Non-corrosive
- 360° valve

TYPICAL PROPERTIES

Contents	Unit	400 ml
Basis		Organic solvents
Density	g/ml	0.778
Propellant		Propane/butane
Colour	Visual	Transparent
Vapor Pressure at 20 °C	Bar	5.5 to 6.5
Flash Point	°C	21
Volume organic component (VOC)	%	99
pH		Neutral
Yield	g/sec	3.8